

USER MANUAL

Z-8AI

SENECA s.r.l.

Via Austria, 26 – 35127 – PADOVA – ITALY

Tel. +39.049.8705355 – 8705359 Fax. +39.049.8706287

Web site: www.seneca.it

Technical assistance: supporto@seneca.it (IT), support@seneca.it (Other)

Commercial reference: commerciale@seneca.it (IT), sales@seneca.it (Other)



This document is property of SENECA srl. Duplication and reproduction of its are forbidden (though partial), if not authorized. Contents of present documentation refers to products and technologies described in it. Though we strive for reach perfection continually, all technical data contained in this document may be modified or added due to technical and commercial needs; it's impossible eliminate mismatches and discordances completely. Contents of present documentation is anyhow subjected to periodical revision. If you have any questions don't hesitate to contact our structure or to write us to e-mail addresses as above mentioned.

MI00259-3-EN

Seneca Z-PC Line module: Z-8AI


The Z-8AI module acquires up to 8 single-ended input signals (voltage or current type) and it converts them to a digital format (normalized measure).

General characteristics

- It is possible to choose if each input is voltage or current type
- It is possible to enable/disable each input
- It is possible to change: the electrical start/end scale between $\pm 10\text{ V}$, $\pm 20\text{ mA}$, the normalized start/end scale between ± 32000
- Configuration of the module (node) address and baud-rate by Dip-Switches
- It is possible to add/remove the module to/from RS485-bus without disconnecting the communication or power supply
- It is possible to switch automatically RS485 to RS232 or vice versa

Features

INPUT	
Number	8
Resolution	16 bits (15+1 sign). If Electrical End-Scale (E.E.S.) $<2.5\text{V}$, resolution= $80\mu\text{V}$; se $2.5\text{V}<\text{E.E.S.}<10\text{V}$, resolution= $300\mu\text{V}$
Sampling time	Configurable between: 10, 20, 40 or 120 ms
Max Refresh Speed	10 ms for enabled channel + a fixed 10 ms for Modbus communication time. Examples: 1 channel configured: Max Refresh speed 20 ms 2 channels configured: Max Refresh speed 30 ms ... 8 channels configured: Max Refresh speed 90 ms
Accuracy	Initial: 0.1% of E.E.S.. If E.E.S. $<2.5\text{V}$, accuracy= 2.5mV ; if $2.5\text{V}<\text{E.E.S.}<10\text{V}$, accuracy= 10mV Linearity: 0.03% of E.E.S. (see initial accuracy) Zero: 0.05% of E.E.S. (see initial accuracy) Thermal stability: $< 100\text{ ppm}/^\circ\text{K}$ EMI: $< 1\%$
Protection	$\pm 30\text{Vdc}$ and 25mA
Voltage-type IN	Bipolar with E.S.S./E.E.S.(Electrical Start/End Scale) configurable between: $\pm 10\text{Vdc}$. Input impedance: $> 100\text{ k}\Omega$
Current-type IN	Bipolar with E.S.S./E.E.S. configurable between: $\pm 20\text{mA}$. Internal shunt: 50Ω . To enable these shunts, use the «Analog inputs» Dip-Switches
Internal supply Vaux	The #4 and #7 screw terminals: power 13V to max 180mA (figure10)
CONNECTIONS	
RS485 interface	IDC10 connector
RS232 interface	Jack stereo 3.5mm connector: plugs into COM port
1500 Vac ISOLATIONS	
	Between: power supply, ModBUS RS485, analog inputs




The power supply transformer necessary to supply the module must comply with EN60742 (Isolated transformers and safety transformers requirements). To protect the power supply, it is recommended to install a fuse.

Input connections

It is possible to connect to the Z-8AI module two types of sensors:

- **passive sensors**, indicated with “S” label (these sensors have to be supplied: by a module external voltage Vext or by the module internal voltage Vaux);
- **active sensors**, indicated with “voltage generator” or “current generator” label (these sensors have already been supplied).

In the following figure are shown five possible sensor connections.



	Acquired signal	Up to	Connection modality	Sensors power supply
A	Voltage or current type	8 passive sensors	3-wire	Vaux (*)
B	Voltage type	8 sensors as voltage generator	2-wire	/
C	Current type	8 sensors as current generator	2-wire	/
D	Current-active type	8 passive sensors	2-wire	Vaux (*)
E	Current-passive type	8 passive sensors	2-wire	Vext (connect “-” to GND)



(*) A and D connections are possible only if the absorbed currents sum from all sensors: <180mA.

Dip-switches table



In the following tables: box without circle means Dip-Switch=0 (OFF state); box with circle means Dip-Switch=1 (ON state).

BAUD-RATE (Dip-Switches: DIP-SWITCH STATUS)						
1	2	Meaning				
		Baud-rate=9600 Baud				
	●	Baud-rate=19200 Baud				
●		Baud-rate=38400 Baud				
●	●	Baud-rate=57600 Baud				
ADDRESS (Dip-Switches: DIP-SWITCH STATUS)						
3	4	5	6	7	8	Meaning
						Address and Baud-Rate are acquired from memory(EEPROM)
					●	Address=1
				●		Address=2
				●	●	Address=3
			●			Address=4
X	X	X	X	X	X
●	●	●	●	●	●	Address=63
RS485 TERMINATOR (Dip-Switches: DIP-SWITCH STATUS)						
9	10	Meaning				
		RS485 terminator disabled				
	●	RS485 terminator enabled				

INPUT TYPE (Dip-Switches: ANALOG INPUTS)								
1	2	3	4	5	6	7	8	Meaning
								IN 1=voltage
●								IN 1=current
	●							IN 2=voltage
		●						IN 2=current
			●					IN 3=voltage
				●				IN 3=current
					●			IN 4=voltage
						●		IN 4=current

INPUT TYPE (Dip-Switches: ANALOG INPUTS)								
1	2	3	4	5	6	7	8	Meaning
								IN 5=voltage
				●				IN 5=current
								IN 6=voltage
					●			IN 6=current
								IN 7=voltage
						●		IN 7=current
								IN 8=voltage
							●	IN 8=current

RS485 Register table

Name	Range	Interpretation of register	R/W	Default	Address
MachineID	/	MSB, LSB	R		40001
	Id_Code (Module ID)			0x0E	Bit [15:8]
	Ext_Rev (Module version)				Bit [7:0]
FWREV	/	Word	R		40062
	Firmware Code				
Status	/	Bit	R/W		40002
	Generic error: 0=there isn't; 1=there is			/	Bit 15
	Configuration error: 0=there isn't; 1=there is			/	Bit 14
	Memory error (EEPROM): 0=there isn't; 1=there is			/	Bit 13
	Save configuration in memory (EEPROM): 0=deactivated; 1=activated			/	Bit 12
	These bits aren't used			/	Bit [11:9]
	Reset of module: 0=deactivated; 1=activated			/	Bit 8
	These bits aren't used			/	Bit [7:0]
Errors	/	Bit	R		40063
	These bits aren't used			/	Bit[15:10]
	Setting error (in memory): 0=there isn't; 1=there is			/	Bit 9
	Calibration error (in memory): 0=there isn't; 1=there is			/	Bit 8
	These bits aren't used			/	Bit [7:1]
	ADC error: 0=there isn't; 1=there is			/	Bit 0
Address Parity	/	MSB, LSB	R/W		40012
	Address for RS485 (address of module/node if parameters are configured by memory modality): from 0x01=1 to 0xFF=255			1	Bit [15:8]
	Parity for RS485: 0=there isn't; 1=even parity; 2=odd parity			0	Bit [7:0]
Baudrate Delay	/	MSB, LSB	R/W		40013
	Baud-rate for RS485 (baud-rate of module/node if parameters are configured by memory modality): 0=4800; 1=9600; 2=19200; 3=38400; 4=57600; 5=115200; 6=1200; 7=2400			38400	Bit [15:8]
	Delay for RS485 (delay of communication response: it represents the number of the pauses(*) between the end of Rx message and the start of Tx message): from 0x00=0 to 0xFF=255 (*)1 pause=6 characters			0	Bit [7:0]
INPUT 1					
IN1	Between: IN 1-NSS, IN 1-NES	Word	R		40003
	Normalized measure of input 1			/	
IN 1-ESS	±10000 [mV] (if voltage), ±20000 [µA] (if current)	Word	R/W		40014
	Electrical Start Scale (E.S.S.) of input 1 [mV or µA]			0 [mV]	
IN 1-EES	±10000 [mV] (if voltage), ±20000 [µA] (if current)	Word	R/W		40015
	Electrical End Scale (E.E.S.) of input 1 [mV or µA]			10000 [mV]	
IN 1-NSS	±32000	Word	R/W		40016

	Normalized Start Scale (N.S.S.) of input 1			0	
IN 1-NES	± 32000	Word	R/W		40017
	Normalized End Scale (N.E.S.) of input 1			10000	
IN 1-FLAGS	/	Bit	R/W		40019
	These bits aren't used			/	Bit [15:8]
	Input enabling: 0=deactivated; 1=activated			1	Bit 7
	These bits aren't used			/	Bit [6:4]
	Sampling time: 0b00=10 ms; 0b01=30 ms; 0b10=40 ms; 0b11=120 ms			10 [ms]	Bit [3:2]
	This bit isn't used			/	Bit 1
	Acquired-input type: 0=voltage; 1=current			0	Bit 0
INPUT 2					
IN 2	Between: IN 2-NSS, IN 2-NES	Word	R		40004
	Normalized measure of input 2			/	
IN 2-ESS	± 10000 [mV] (if voltage), ± 20000 [μ A] (if current)	Word	R/W		40020
	Electrical Start Scale (E.S.S.) of input 2 [mV or μ A]			0 [mV]	
IN 2-EES	± 10000 [mV] (if voltage), ± 20000 [μ A] (if current)	Word	R/W		40021
	Electrical End Scale (E.E.S.) of input 2 [mV or μ A]			10000 [mV]	
IN 2-NSS	± 32000	Word	R/W		40022
	Normalized Start Scale (N.S.S.) of input 2			0	
IN 2-NES	± 32000	Word	R/W		40023
	Normalized End Scale (N.E.S.) of input 2			10000	
IN 2-FLAGS	/	Bit	R/W		40025
	See IN 1-FLAGS register (40019)			/	
INPUT 3					
IN 3	Between: IN 3-NSS, IN 3-NES	Word	R		40005
	Normalized measure of input 3			/	
IN 3-ESS	± 10000 [mV] (if voltage), ± 20000 [μ A] (if current)	Word	R/W		40026
	Electrical Start Scale (E.S.S.) of input 3 [mV or μ A]			0 [mV]	
IN 3-EES	± 10000 [mV] (if voltage), ± 20000 [μ A] (if current)	Word	R/W		40027
	Electrical End Scale (E.E.S.) of input 3 [mV or μ A]			10000 [mV]	
IN 3-NSS	± 32000	Word	R/W		40028
	Normalized Start Scale (N.S.S.) of input 3			0	
IN 3-NES	± 32000	Word	R/W		40029
	Normalized End Scale (N.E.S.) of input 3			10000	
IN 3-FLAGS	/	Bit	R/W		40031
	See IN 1-FLAGS register (40019)			/	
INPUT 4					
IN 4	Between: IN 4-NSS, IN 4-NES	Word	R		40006
	Normalized measure of input 4			/	
IN 4-ESS	± 10000 [mV] (if voltage), ± 20000 [μ A] (if current)	Word	R/W		40032
	Electrical Start Scale (E.S.S.) of input 4 [mV or μ A]			0 [mV]	
IN 4-EES	± 10000 [mV] (if voltage), ± 20000 [μ A] (if current)	Word	R/W		40033
	Electrical End Scale (E.E.S.) of input 4 [mV or μ A]			10000 [mV]	
IN 4-NSS	± 32000	Word	R/W		40034
	Normalized Start Scale (N.S.S.) of input 4			0	
IN 4-NES	± 32000	Word	R/W		40035

	Normalized End Scale (N.E.S.) of input 4			10000	
IN 4-FLAGS	/	Bit	R/W		40037
	See IN 1-FLAGS register (40019)			/	
INPUT 5					
IN 5	Between: IN 5-NSS, IN 5-NES	Word	R		40007
	Normalized measure of input 5			/	
IN 5-ESS	±10000 [mV] (if voltage), ±20000 [µA] (if current)	Word	R/W		40038
	Electrical Start Scale (E.S.S.) of input 5 [mV or µA]			0 [mV]	
IN 5-EES	±10000 [mV] (if voltage), ±20000 [µA] (if current)	Word	R/W		40039
	Electrical End Scale (E.E.S.) of input 5 [mV or µA]			10000 [mV]	
IN 5-NSS	±32000	Word	R/W		40040
	Normalized Start Scale (N.S.S.) of input 5			0	
IN 5-NES	±32000	Word	R/W		40041
	Normalized End Scale (N.E.S.) of input 5			10000	
IN 5-FLAGS	/	Bit	R/W		40043
	See IN 1-FLAGS register (40019)			/	
INPUT 6					
IN 6	Between: IN 6-NSS, IN 6-NES	Word	R		40008
	Normalized measure of input 6			/	
IN 6-ESS	±10000 [mV] (if voltage), ±20000 [µA] (if current)	Word	R/W		40044
	Electrical Start Scale (E.S.S.) of input 6 [mV or µA]			0 [mV]	
IN 6-EES	±10000 [mV] (if voltage), ±20000 [µA] (if current)	Word	R/W		40045
	Electrical End Scale (E.E.S.) of input 6 [mV or µA]			10000 [mV]	
IN 6-NSS	±32000	Word	R/W		40046
	Normalized Start Scale (N.S.S.) of input 6			0	
IN 6-NES	±32000	Word	R/W		40047
	Normalized End Scale (N.E.S.) of input 6			10000	
IN 6-FLAGS	/	Bit	R/W		40049
	See IN 1-FLAGS register (40019)			/	
INPUT 7					
IN 7	Between: IN 7-NSS, IN 7-NES	Word	R		40009
	Normalized measure of input 7			/	
IN 7-ESS	±10000 [mV] (if voltage), ±20000 [µA] (if current)	Word	R/W		40050
	Electrical Start Scale (E.S.S.) of input 7 [mV or µA]			0 [mV]	
IN 7-EES	±10000 [mV] (if voltage), ±20000 [µA] (if current)	Word	R/W		40051
	Electrical End Scale (E.E.S.) of input 7 [mV or µA]			10000 [mV]	
IN 7-NSS	±32000	Word	R/W		40052
	Normalized Start Scale (N.S.S.) of input 7			0	
IN 7-NES	±32000	Word	R/W		40053
	Normalized End Scale (N.E.S.) of input 7			10000	
IN 7-FLAGS	/	Bit	R/W		40055
	See IN 1-FLAGS register (40019)			/	
INPUT 8					
IN 8	Between: IN 8-NSS, IN 8-NES	Word	R		40010
	Normalized measure of input 8			/	
IN 8-ESS	±10000 [mV] (if voltage), ±20000 [µA] (if current)	Word	R/W		40056
	Electrical Start Scale (E.S.S.) of input 8 [mV or µA]			0 [mV]	

IN 8-EES	± 10000 [mV] (if voltage), ± 20000 [μ A] (if current)	Word	R/W		40057
	Electrical End Scale (E.E.S.) of input 8 [mV or μ A]			10000 [mV]	
IN 8-NSS	± 32000	Word	R/W		40058
	Normalized Start Scale (N.S.S.) of input 8			0	
IN 8-NES	± 32000	Word	R/W		40059
	Normalized End Scale (N.E.S.) of input 8			10000	
IN 8-FLAGS	/	Bit	R/W		40061
	See IN 1-FLAGS register (40019)			/	

Easy-SETUP

To configure the Seneca Z-PC Line modules, it is possible to use Easy-SETUP software,

Free-downloadable from the www.seneca.it; the configuration can be performed by USB port.

ModBUS registers

Modbus registers: Holding registers		
Register	Name	Description
40003	IN CH1	Channel measurement value with scale ± 10000 normalised.
40004	IN CH2	Channel measurement value with scale ± 10000 normalised.
40005	IN CH3	Channel measurement value with scale ± 10000 normalised.
40006	IN CH4	Channel measurement value with scale ± 10000 normalised.
40007	IN CH5	Channel measurement value with scale ± 10000 normalised.
40008	IN CH6	Channel measurement value with scale ± 10000 normalised.
40009	IN CH7	Channel measurement value with scale ± 10000 normalised.
40010	IN CH8	Channel measurement value with scale ± 10000 normalised.